



ARTURIA ORIGIN SPECIFICATIONS

Maximum Polyphony	(32) voices
Data Format	24-bit, 44.1 kHz
Patch Memory	(1,000) Programs, (256) Multis; (4) Programs per Multi
Audio Inputs	(2) balanced ¼" TRS
Audio Outputs	(2) balanced ¼" TRS main, (8) balanced ¼" TRS individual, (1) ¼" stereo headphone, (1) coaxial S/PDIF
MIDI I/O	(1) In, (1) Out, (1) Thru, (1) USB 2.0
Control Inputs	(1) ¼" footpedal, (1) ¼" footswitch
Effects	(3) inserts maximum per Program, (12) inserts maximum per Multi; chorus, delay, reverb, distortion, phaser
Onboard Sequencing	(3) 32-step sequencers per program (one-shot, loop, forward, backward, forward/backward)
Arpeggiator Modes	forward, backward, forward/backward, random
Display	320 x 236-pixel color LCD
Power	6.5 VDC adapter
Dimensions	19" (W) x 3.5" (H) x 11.5" (D)
Weight	17 lbs.