

## Roland Juno-Stage Specifications

Keyboard	76-note, velocity
Sound Engine	16-bit linear PCM sample playback
Outputs	(2) unbalanced ¼" TS, (1) ¼" headphones, (1) ¼" Song/Click Out
Input	(1) combo 1/4" unbalanced/XLR balanced with 48V phantom power
Control Connections	(1) USB 2.0, (1) MIDI In, (1) MIDI Out, (1) patch select, (1) expression pedal, (1) sustain switch
Voice Allocation	128-voice polyphonic, 16-part multitimbral
Waveform ROM	128 MB, (2) SRX expansion slots
Presets	(1,027) user Patches, (256) GM2 Patches, (32) user Rhythm Sets, (9) GM2 Rhythm Sets
Effects	MFx (multi-effects), (3) simultaneous, (79) types; chorus, (3) types; reverb, (5) types; mic-input reverb, (8) types
Sequencing	playback only, SMF (Types 0 and 1), AIFF/WAV/MP3; arpeggiator, (128) factory presets, (128) user presets; rhythm patterns, (256) preset, (256) user
Real-Time Controllers	(1) pitch bend/modulation lever, (1) D Beam, (2) assignable switches
Display	(1) 240x64-pixel backlit monochrome graphic LCD
Power	9 VDC AC adapter
Dimensions	49.25" (W) x 13.56" (D) x 4.44 (H)
Weight	21.63 lbs.